



MIC-10

Index: WMGBMIC10

Insulation Resistance Meter

Description

- Insulation resistance measurement:
 - selected test voltage: 50, 100, 250, 500, 1000 V,
 - continuous indication of insulation resistance or leakage current,
 - automatic discharge of capacitance of tested object after the insulation resistance measurement,
 - acoustic signalling of five-second periods to facilitate obtaining time characteristics,
 - indication of actual test voltage during the measurement,
 - protection against measuring live objects,
 - three-lead measurement.
- Continuity measurement of protective and equipotential conductors according to EN 61557 - 4 with the >200 mA current
- Low-voltage circuit continuity and resistance measurement:

- circuit resistance measurement (<1999) with the <15 mA current,
- quick sound signal if circuit resistance is below 30 .
- Capacitance measurement during the R_{ISO} measurement
- Measurement of alternating and direct voltages in the 0...600 V range.
- Power supply: 4 AA disposable or rechargeable batteries, monitoring of power supply voltage.
- Meter conform to EN 61557.

Specifications

Electric safety:

- type of insulation: double, according to EN 61010 - 1 and IEC 61557
- measurement category: IV 600 V (III 1000 V) according to EN 61010 - 1
- protection class acc. to EN 60529: IP67

Other technical specifications:

- power suply: 4 alkaline batteries or or battery package Ni-MH
- weight: ~1 kg
- dimentions: 220 x 100 x 60 mm

Insulation resistance measurement

Measuring range according to EN 61557 - 2 for $U_N=50$ V: 50 k ...250,0 M

Range	Resolution	Accuracy
0,0...999,9 k	0,1 k	$\pm (3\% \text{ m.v.} + 8 \text{ digits})$
1,000...9,999 M	0,001 M	
10,0...99,99 M	0,01 M	
100,0...250,0 M	0,1 M	

Measuring range according to EN 61557 - 2 for $U_N=100$ V: 100 k ...500,0 M

Range	Resolution	Accuracy
0,0...999,9 k	0,1 k	$\pm (3\% \text{ m.v.} + 8 \text{ digits})$
1, 000...9,999 M	0,001 M	
10,0...99,99 M	0,01 M	
100,0...500,0 M	0,1 M	

Measuring range according to EN 61557 - 2 for $U_N=250$ V: 250 k ...2,000 G

Range	Resolution	Accuracy
0,0...999,9 k	0,1 k	$\pm (3\% \text{ m.v.} + 8 \text{ digits})$
1,000...9,999 M	0,001 M	

10,0...99,99 M	0,01 M	
100,0...999,0 M	0,1 M	
1,000...2,000 G	0,001 G	

Measuring range according to PN-EN 61557 - 2 for $U_N=500$ V: 500 k ...5,00 G

Range	Resolution	Accuracy
0,0...999,9 k	0,1 k	$\pm (3\% \text{ m.v.} + 8 \text{ digits})$
1,000...9,999 M	0,001 M	
10,00...99,99 M	0,01 M	
100,0...999,0 M	0,1 M	
1,000...5,000 G	0,001 G	$\pm (4\% \text{ m.v.} + 6 \text{ digits})$

Measuring range according to EN 61557 - 2 for $U_N=1000$ V: 1000 k ...10,00 G

Range	Resolution	Accuracy
0,0...999,9 k	0,1 k	$\pm (3\% \text{ m.v.} + 8 \text{ digits})$
1,000...9,999 M	0,001 M	
10,00...99,99 M	0,01 M	
100,0...999,0 M	0,1 M	
1,000...5,000 G	0,001 G	$\pm (4\% \text{ m.v.} + 6 \text{ digits})$
5,00...10,00 G	0,01 G	

Continuity measurement of protective and equipotential conductors with the 200 mA current

Measuring range according to EN 61557 - 4: 0,10...1999

Range	Resolution	Accuracy
0,00...19,99	0,01	$\pm (2\% \text{ m.v.} + 3 \text{ digits})$
20,0...199,9	0,1	
200...1999	1	$\pm (4\% \text{ m.v.} + 3 \text{ digits})$

- Voltage on open terminals: <8 V
- Output current at $R < 2 \Omega : I_{SC} > 200$ mA: $I_{SC} > 200$ mA
- Compensation of test leads' resistance
- Unidirectional current flow

Low-voltage and resistance measurement

Range	Resolution	Accuracy
0,0...199,9	0,1	$\pm (3\% \text{ m.v.} + 3 \text{ digits})$
200...1999	1	

- Voltage on open terminals: <8 V
- Current for closed terminals $5 \text{ mA} < I_{SC} < 15 \text{ mA}$
- Sound signal and green LED on when measured resistance $< 30 \Omega \pm 50\%$
- Compensation of test leads' resistance,

Capacitance measurements

Range	Resolution	Accuracy
1...999 nF	1 nF	$\pm (5\% \text{ m.v.} + 5 \text{ digits})$
1,00...9,99 μF	0,01 μF	

- Capacitance value displayed during the R_{ISO} measurement
- For test voltages below 100 V and measured resistance below $10 \text{ M}\Omega$, unspecified capacitance measurement error

Measurement of alternating and direct voltage

Range	Resolution	Accuracy
0,0...299,9 V	0,1 V	$\pm (2\% \text{ m.v.} + 6 \text{ digits})$
300...600 V	1 V	$\pm (2\% \text{ m.v.} + 2 \text{ digits})$

- Frequency range: 45...65 Hz